

# RCDT300 Series

## Residual Current Device Testers



- Tests standard, DC, selective, and programmable RCDs
- Ramp testing
- Auto (Remote) testing
- 3 Phase safe
- Enables testing on 110 V centre tapped supplies.
- Tough rubber armoured case with built-in cover
- Weatherproof to IP54
- USB interface for downloading test result

### DESCRIPTION

#### Standard test ranges

- The RCDT300 series can perform 1/2I, 1xI and 5xI tests on RCDs rated at 30 mA, 100 mA, 300 mA and 500 mA on general and selective (time delayed) RCDs. The RCDT320/330 can also test RCDs rated at 10 mA and 1000 mA. All units offer DC testing of RCD's.

- Test times for normal and Selective RCDs are:

	Normal		Selective	
1/2I	2s		2s	
I	300ms		2s	
5I	40ms		150ms	

- 5I tests are available on RCDs rated up to 100 mA.

#### Polarity

- All RCDs can be tested at 0° or 180°

#### Selective RCDs

- Selective breakers have a time delay in tripping. When selected, trip test times are extended and a 30s delay is allowed between the measurement of the fault voltage and the application of the test current.

#### Touch voltage

- Touch voltage is measured at the start of the RCD test. If enabled it is displayed on the analogue arc on completion of testing.

Touch voltage inhibit is selectable from 25 V or 50 V.

#### Tough:-

- Designed to take the bashing that testers receive on site, the Megger RCDT testers are rubber armoured.
- The rigid display cover folds right out of the way during testing and locks down to protect the display when it is finished.

#### Simple to use:-

- No buried functions mean it is obvious how to use the Megger RCDT.
- Colour coded ranges help test range selection, reducing test times and fault location.
- A user guide in the lid provides all the basic information.

#### Hands free use:-

- It hangs comfortably around the neck for hands-free use because the instrument is carefully balanced.

#### DC sensitive RCDs

- DC sensitive RCDs can be tested at 1/2I, 1xI and 5xI.

#### Ramp testing (RCDT320/330)

- To measure the trip current of an RCD. Current level is slowly increased from 1/2I to 1I (+10%). When the RCD trips the trip current is displayed and held on the screen.
- Very useful diagnosing nuisance tripping of RCDs.

**Auto testing (RCDT320/330)**

- Where the RCD under test and tester need to be in different locations, the user connects the RCDT320/330 to the circuit and goes to standby the RCD under test to reset it. The RCDT320/330 will automatically perform a 1/2I, I and 5I test at both 0° and 180°. The RCD is reset each time it trips by the electrician and the tester proceeds to the next test automatically. All results are displayed at the end of the test, saving you time and energy

The RCDT330 adds the ability to test Programmable RCDs to the test options available, covering the range from 10 mA to 1000 mA, with step increments starting at 1 mA.

The RCDT330 additionally offers the facility to save test results to internal memory. Over 1000 result can be saved on site, and downloaded to a computer when convenient. Data is stored in non-volatile memory, being retained when the instrument is switched off or batteries are exhausted.

A Job reference number can be selected for a range of results, allowing separate locations to be tested with the same tester and easily separated when downloaded.

A memory bar graph acts as a 'Fuel Gauge' showing how much memory has been used

Test results are downloaded to CSV (Comma Separated Variable) spreadsheets, and can be imported into Microsoft Excel. If certificates or reports are required, the results can be downloaded directly into Megger Powersuite Professional with a range of features for creating professionally finished documentation for NICEIC, ECA BS and other standard formats.

**Safety features:-** To protect the user and the tester from incorrect use the RCDT series all has an extensive range of features known as Megger Intelligent Safety System including:

- LED connection indicators – show test lead connections and supply status
- Safety Interlock – prevents unsafe connection of test leads
- 3 Phase safe - Even if the RCDT is connected across phases, the instruments will remain safe and not be damaged.
- Test inhibit – If supply voltage exceeds 300V testing will be inhibited.

All the Megger RCDT300 series RCD testers meet or exceed the UK and International Wiring Regulations, including requirements of BS7671 and VDE 0413 parts 1 and 4, HD 384, IEC 364, NFC15-100, and NEN3140, ES59009, AS/NZS 3000 and EN 61557.

In addition the range meets the requirements of IEC 61010-1 for safe connection to Category III supply (300 V Phase to Earth).

The new Megger electrician's testers are simple, no fuss electrical testers that are tough, reliable and easy to use.

Available in separate instruments, the series consists of the:

- MIT300 range
- LT300 range
- RCDT300 range
- Insulation and continuity
- Loop testing
- RCD testing

Between them they meet all the requirements for modern electrical testing.

	RCDT310	RCDT320	RCDT330
<b>RCD testing</b>			
1/2I, I, 5I RCD trip time test	■	■	■
Selective breakers	■	■	■
DC breakers (1/2 I, I, 5I)	■	■	■
30, 100, 300, 500 mA RCDs	■	■	■
10 mA /1 A RCDs		■	■
RCD trip current test (RAMP)		■	■
Auto sequence test		■	■
0°/180° polarity selection	■	■	■
Touch voltage display inhibit (selectable)	■	■	■
Max Touch voltage (25V/50 V)	■	■	■
Operating range 100 to 280 V	■		
Operating range 50 to 280 V		■	■
Programmable RCDs			■
Frequency measurement		■	■
<b>Features</b>			
3 Phase Safe	■	■	■
Large clear display	■	■	■
Backlight		■	■
Battery status indication	■	■	■
Auto power down	■	■	■
Fuse blown indication	■	■	■
IP54 weatherproof	■	■	■
Result storage			■
Downloading			■
USB interface			■
IEC61010-1 CATIII 300 V	■	■	■
EN61557	■	■	■
Calibration Certificate	■	■	■
3 year warranty	■	■	■
<b>Accessories</b>			
Plug ended test lead	■	■	■
2 wire ended test lead probe/croc clip ended		■	■

**SPECIFICATIONS**

**RCD Test Ranges (to EN61557-6)**

**Supply voltage**

**Supply:** RCDT310 100 V - 280 V 45Hz to 65 Hz  
RCDT320 50 V - 280 V 45Hz to 65 Hz  
RCDT330 50 V - 280 V 45 Hz to 65 Hz

**Test Current Accuracy:**

**No Trip Test:** (1/2I) -8% to -2%

**Trip Test:** (I, 5I) +2% to +8%

**Trip Time:** ±1% ±1ms

**Voltage measurement**

(All Models)

**Range ac:** 0V - 300V 25Hz to 450Hz

**Accuracy:** ±2% ±2 digits

**Frequency measurement**

(RCDT320/330)

**Range:** 25Hz to 450Hz

**Accuracy:** 25.0Hz to 199.9Hz ±0.1Hz

200Hz to 450Hz ±1Hz

**Fault (Touch) Voltage**

**Displayed range:**

0 V to 50 V

**Error:**

+5%/+15% ±0.5 V

**Programmable RCD step Increments**

10 mA to 50 mA - 1 mA steps

50 mA to 500 mA - 5 mA steps

500 mA to 1000 mA - 10 mA steps

**Test result storage (1000 results)**

Job Number 256 locations

Distribution Board no. 99 locations

Circuits 99 locations

Phases P1, P2, P3

Last recorded result may be recalled to the display. All data can be downloaded to a PC using Download Manager (supplied) or Megger Powersuite Professional Windows software

**Temperature and humidity**

**Operating Range:** -5°C to +40°C

**Operating Humidity:** 93% R.H. at +40°C max.

**Storage Range:** -25°C to +70°C

**Maximum altitude:** 2000m

**Environmental Protection:** IP54

**Communications**

USB interface

**Safety**

Meets the requirements of IEC61010-1 Cat III 300V phase to earth.

**IEC61557**

Complies with the following parts of EN61557, Electrical safety in low voltage systems up to 1000 V ac and 1500 V dc- Equipment for testing, measuring or monitoring of protective measures:

Part1-General Requirements

Part4-Residual current devices

**Power supply**

**Batteries:** 8 x 1,5 V cells IEC LR6 type (AA alkaline).

**Rechargeable:** 8 x 1.2 V NiCd or NiMH cells.

**Battery Life:** 2000 consecutive tests

**Weight**

All units 980gms

**Dimensions**

All units 203 x 148 x 78 mm

**E.M.C.**

In accordance with IEC61326-1

<b>ORDERING INFORMATION</b>			
<b>Item (Qty)</b>	<b>Order Code</b>	<b>Item (Qty)</b>	<b>Order Code</b>
RCDT310 RCD Tester 30, 100, 300, 500 mA	RCDT310-EN-BS	RCDT310 RCD Tester 30, 100, 300,500 mA	RCDT310-EN-SC
<b>Included Accessories</b>		<b>Included Accessories</b>	
Mains plug test lead (BS1363)	6220-740	Mains plug test lead (CEE 7/7)	6220-741
RCDT320 RCD Tester 10, 30, 100, 300, 500,1000 mA	RCDT320-EN-BS	RCDT320 RCD Tester 10, 30, 100, 300, 500,1000 mA	RCDT320-EN-SC
<b>Included Accessories</b>		<b>Included Accessories</b>	
Mains plug test lead (BS 1363)	6220-740	Mains plug test lead (CEE 7/7)	
Test lead set and crocodile clips	6220-784	Test lead set and crocodile clips (2 wire)	6220-784
RCDT330 RCD Tester 10, 30, 100, 300, 500,1000 mA	RCDT330-EN-BS	RCDT330 RCD Tester 10, 30, 100, 300, 500,1000 mA	RCDT330-EN-SC
<b>Included Accessories</b>		<b>Included Accessories</b>	
Mains plug test lead (BS 1363)	6220-740	Mains plug test lead (CEE 7/7)	
Test lead set and crocodile clips	6220-784	Test lead set and crocodile clips (2 wire)	6220-784
RCDT310 RCD Tester 30, 100, 300, 500 mA	RCDT310-EN-AU	<b>Optional Accessories for all RCDT's</b>	
<b>Included Accessories</b>		Test lead set and crocodile clips (2 wire)	6220-784
Mains plug test lead (AS/NZS 3112)	6220-790	BS = BS1363 plug	
RCDT320 RCD Tester 10, 30, 100, 300, 500,1000 mA	RCDT320-EN-AU	AU = AS/NZ253112 plug	
<b>Included Accessories</b>		SC = CEE7/7 plug	
Mains plug test lead (AS/NZS 3112)	6220-790		
Test lead set and crocodile clips	6220-784		
RCDT330 RCD Tester 10, 30, 100, 300, 500,1000 mA	RCDT330-EN-AU		
<b>Included Accessories</b>			
Mains plug test lead (AS/NZS 3112)	6220-790		
Test lead set and crocodile clips	6220-784		

**UK**  
Archcliffe Road Dover  
CT17 9EN England  
T +44 (0) 1304 502101  
F +44 (0) 1304 207342

**UNITED STATES**  
4271 Bronze Way  
Dallas T X75237-1019 USA  
T 800 723 2861 (USA only)  
T +1 214 333 3201  
F +1 214 331 7399

**OTHER TECHNICAL SALES OFFICES**  
Norristown USA, Toronto CANADA,  
Mumbai INDIA, Trappes FRANCE,  
Sydney AUSTRALIA, Madrid SPAIN  
and the Kingdom of BAHRAIN.

Registered to ISO 9001:2000 Reg no. Q 09290  
Registered to ISO 14001 Reg no. EMS 61597  
**RCDT300\_DS\_en\_V03**  
**www.megger.com**  
Megger is a registered trademark